



THALIA LE-B QUICK START MENU

START

PRESS THE [OK] BUTTON ONCE TO ENTER THE QUICK START MENU.

STEP 1...

THE SCREEN WILL DISPLAY "LANG" (LANGUAGE)...

...2...

...PRESS THE [-] BUTTON TO SCROLL DOWN TO "ENG" (ENGLISH) AND THEN PRESS [OK]

...3...

NEXT YOU SELECT THE TYPE OF MOTOR...

...4...

PRESS THE [-] BUTTON TO SCROLL DOWN...

- ELI 250 BT... ELI
- PHOBOS BT... PHOb
- IGEA BT... IGER
- LUX BT... LUH
- LUX G BT... LUH9
- SUB BT... SUB

...AND THEN PRESS THE [OK] BUTTON

...5...

THEN SELECT THE NUMBER OF MOTORS CONNECTED...

...6...

"1" OR "2" AND PRESS [OK]

...7...

NEXT, DETERMINE THE OPENING DIRECTION...

...8...

SELECT "INT" FOR PULL-TO-OPEN, OR "EXT" FOR PUSH-TO-OPEN. THEN PRESS [OK]

...9...

THE SCREEN WILL THEN DISPLAY "PRESET"...

...10...

SCROLL DOWN USING THE [-] BUTTON AND SELECT YOUR PRESET, "AR", "SR", "AC", "SC" OR "IND" BASED ON THE LOGIC FEATURES ON THE TABLE BELOW.

LOGIC PRESETS	AR	SR	AC	SC	IND
	AUTOMATIC RESIDENTIAL	SEMI-AUTOMATIC RESIDENTIAL	AUTOMATIC COMMERCIAL	SEMI-AUTOMATIC COMMERCIAL	INDUSTRIAL
AUTOMATIC CLOSING TIMER	X		X		
PRE-ALARM			X	X	
UNINTERRUPTED OPEN CYCLE			X	X	
INSTANT REVERSE ON CLOSING	X		X		
HOLD TO RUN					X
QUICK REMOTE PROGRAMMING	X	X	X	X	

...THEN PRESS [OK].

...12...

THE SCREEN WILL THEN READ "LSW ADJUST" IF LUX OR LUX G WAS SELECTED.

...13...

"OPM1" (OPEN MOTOR 1) WILL BE DISPLAYED ON THE SCREEN

...14...

MANUALLY OPEN THE GATE...

...15...

PRESS [OK]. IF 2 MOTORS WERE SELECTED, "OPM2" WILL SHOW. PRESS [OK] AGAIN...

...16...

IF 2 MOTORS WERE SELECTED, "CLM2" WILL SHOW. OTHERWISE "CLM1" WILL BE SHOWN.

...17...

MANUALLY CLOSE THE GATE AND LOCK IN POSITION...

...18...

PRESS [OK]. IF 2 MOTORS WERE SELECTED, PRESS [OK] ONCE MORE.

...19...

THE SCREEN WILL READ "OK". PRESS [OK] TO CONTINUE..

...20...

THE WORD "AUTOSET" WILL SCROLL ACROSS THE SCREEN

UPON PRESSING [OK], THE GATE WILL OPEN AND CLOSE AUTOMATICALLY

...21...

NEXT, THE SCREEN WILL THEN READ "MEM REMOTES"

...22...

WHEN THE SCREEN READS "HIDDEN BUTTON"...

...23...

SIMULTANEOUSLY PRESS AND HOLD THE 2 BUTTONS ON YOUR REMOTE UNTIL THE SCREEN READS "RELEASE"

...24...

THE SCREEN WILL THEN READ "DESIRED BUTTON". PRESS THE BUTTON YOU WANT TO OPERATE THE GATE WITH

...25...

THE SCREEN WILL DISPLAY "OK" AND THE NUMBER OF THE REMOTE IN MEMORY. REPEAT THE PROCESS FOR ADDITIONAL REMOTES

...26...

PRESS [OK] TO FINISH SETUP

YOU'RE DONE!!!

For additional information please refer to the installation manual

Technical Assistance 561-995-8155
U.S.A Toll free: 877-995-8155