



ULTRA™
ACCESS CONTROLS

Ultra
Revolution™
Hide

Ultra Aluminum Mfg., Inc.
2124 Grand Commerce Drive
Howell, MI 48855
Phone: 517-548-6755
Toll-Free Phone: 800-656-4420
Toll-Free Fax: 800-643-7429

CONNECT YOUR MAIN GATE WIRES TO "MOTOR 2" TERMINALS (6, 7 & 8)

FOR LEFT-HAND GATE CONNECT WIRE 1 TO TERMINAL 6, WIRE 2 TO TERMINAL 7 AND WIRE 3 TO TERMINAL 8

FOR RIGHT-HAND GATE CONNECT WIRE 1 TO TERMINAL 7, WIRE 2 TO TERMINAL 6 AND WIRE 3 TO TERMINAL 8

IF NEEDED, CONNECT YOUR SECONDARY GATE WIRES TO "MOTOR 1" TERMINALS (3, 4 & 5)

THIS MOTOR WILL OPEN AFTER THE OTHER HAS STARTED

FOR LEFT-HAND GATE CONNECT WIRE 1 TO TERMINAL 3, WIRE 2 TO TERMINAL 4 AND WIRE 3 TO TERMINAL 5

FOR RIGHT-HAND GATE CONNECT WIRE 1 TO TERMINAL 4, WIRE 2 TO TERMINAL 3 AND WIRE 3 TO TERMINAL 5

WIRE #4 (FROM BOTH MOTORS IF 2 ARE INSTALLED) GOES TO TERMINAL 24

CONNECT WIRE 5 TO TERMINAL 11, AND WIRE 6 TO TERMINAL 12 (BOTH MOTORS IF APPLICABLE)

PRESS THE [OK] TWICE TO ENTER PROGRAMMING

IF TWO GATES ARE INSTALLED, SKIP TO THIS STEP

IF ONLY ONE GATE IS CONNECTED, SCROLL DOWN USING [-]. LOOK FOR "LOGIC". THEN PRESS [OK]

ONCE AGAIN, USE [-] TO SCROLL DOWN AND LOOK FOR "1 MOT ON"

PRESS [OK] AND PRESS [+] TO SWITCH "ON". THEN PRESS [OK]

PRESS [+] & [-] AT THE SAME TIME TO GO BACK TO THE MAIN MENU

SCROLL DOWN [-] AND LOOK FOR "LSW ADJUST". PRESS [OK]

"OPM2" (OPEN MOTOR 2) WILL BE DISPLAYED ON THE SCREEN

PRESS THE [+] BUTTON UNTIL THE GATE HAS REACHED ITS OPEN LIMIT.

...THEN PRESS [OK] TO SET THE LIMIT.

IF WHEN PRESSING [+] THE MOTOR MOVES IN THE CLOSING DIRECTION, SWAP WIRES 1 & 2 ON BOTH MOTORS

IF 2 MOTORS WERE SELECTED, "OPM1" WILL SHOW. PRESS [+] TO BRING THE 2ND GATE TO THE FULLY OPEN POSITION...

PRESS [OK] TO SET LIMIT

PRESS THE [-] BUTTON TO CLOSE THE GATE AND HOLD IT UNTIL THE GATE DOES NOT MOVE ANY MORE. PRESS [OK]

THE CLOSE LIMIT IS ADJUSTED PHYSICALLY AT THE GATE

IF TWO GATES ARE INSTALLED, REPEAT THE PREVIOUS STEP FOR THE OPPOSING GATE.

PRESS [OK] TO SET LIMIT

THE SCREEN WILL READ "OK". PRESS [OK] TO CONTINUE..

SCROLL UP [+] TO SEE "AUTOSET". PRESS [OK]

UPON PRESSING [OK], THE GATE WILL OPEN AND CLOSE AUTOMATICALLY 1 TO 3 TIMES

WARNING!
LEFT GATE RIGHT GATE

THE SCREEN WILL READ "OK". PRESS [OK] TO CONTINUE..

SCROLL UP [+] TO "RADIO" AND PRESS [OK]

THE SCREEN WILL READ "ADD START". PRESS [OK] AGAIN

WHEN THE SCREEN READS "HIDDEN BUTTON"...

SIMULTANEOUSLY PRESS AND HOLD THE 2 BUTTONS ON YOUR REMOTE UNTIL THE SCREEN READS "RELEASE"

RELE

THE SCREEN WILL THEN READ "DESIRED BUTTON". PRESS THE BUTTON YOU WANT TO OPERATE THE GATE WITH

THE SCREEN WILL DISPLAY "OK" AND THE NUMBER OF THE REMOTE IN MEMORY.

REPEAT THE PROCESS FOR ADDITIONAL REMOTES

PRESS [+] & [-] AT THE SAME TIME 3 TIMES TO EXIT PROGRAMMING